1

Set up hardware.

www.atiz.com/support/booksnap

Box Contents



Dimension & Weight



Dimension:

Depth: 17 inches Width: 23 inches Height: 34 inches

Weight:

20 kg. (44 lbs.)

34"

Page Size Support

BookSnap supports pages that are within 10 x14 inches. Some supported standard sizes include:



- Maximum size 10" x 14"
- Legal 8" x 14"
- Executive 7.25" x 10.5"
- A5 5.83" x 8.27"
- B5 7.17" x 10.12"
- A4 8.27" x 11.69"
- B4 10.12" x 14.33"
- Envelope monarch 3.88" x 7.5"
- Envelope COM10 4.13" x 9.5"
- Envelope DL 4.33" x 8.66"
- Envelope E5 6.38" x 9.02"
- etc.

Part Identification



How to Assemble



1. Pull the cardboard holder straight up.



3. Use 2 people to lift BookSnap out of the box. Hold the metal structure when lifting.



 Place BookSnap on a table that is level and strong enough to withstand at least 30 kg. (70 lbs.)



2. Place the cardboard holder on the floor.



 Lift BookSnap out of the box as shown.



6. Slowly disassemble the cardboard holder.

How to Assemble



7 The cardboard contains the camera mounts, lamps, bolts, light bulbs, magnetic book holders and hexagon screwdriver.



- 8. Install the camera mount by inserting it into the slot.



 The camera mount once installed should look like this.



11. Put the light bulb in its socket.

10. Install the light bulb into the lamp.



12. Hold lamp with both hands, place it on top on the platform and insert the bolt.

How to Assemble





13. Repeat with the other side.







15. In the box there are 2 pads with magnetic. Those are filters for reducing light reflection on V-Shap's glass. Pads can be installed at both side of the platform.



2

Set up software.

www.atiz.com/support/booksnap

System Requirements

Operating System	Windows XP (Service Pack 2)
CPU	Pentium 1GHz or Better
RAM	Minimum 512MB (2GB is recommended)
Interface	Hi-speed USB 2.0
Driver	Canon Camera Driver
Display	1,024 x 768 pixels/ High Color (16 bit) or Better

Note:

BookSnap comes with 2 software packages:

- 1. BookSnap software (for controlling the cameras)
- 2. BookDrive Editor (for post image processing)

Due to the SDK provided by Canon, BookSnap software currently does not support Windows Vista. It does work only on Windows XP (Service Pack 2).

As for BookDrive Editor, it works on both Windows XP and Windows Vista.

Installation Procedure

1. Close any programs that are running and insert the Atiz software CD into the computer's drive.



If the installation panel does not appear automatically, please use the following procedure.

- 1 Open My Computer
- 2 Right-click the CD-ROM icon and select **Open**.
- 3 Double-click preinstall.exe



2. After a few seconds, you should see the following dialog come up.



3. Select **Easy Installation**. Two software programs will be installed. They are BookSnap software (for capturing images) and BookDrive Editor software (for processing the images).

🙉 BookSnap	Software Installation	
BO	OKSNAP	
	Software Installatio	on
[Easy Installation]
	Custom Installation]
	BookSnap Manual]
		Exit

4. Proceed to next steps by selecting Next.



BookSnap	
Select Installation Folder	Ó
he installer will install BookSnap to the following folder. o install in this folder, click "Next". To install to a different folde	er, enter it below or click "Browse".
Eolder: C:\Program Files\Atiz\BookSnap\	Browse
	Disk Cost
Install BookSnap for yourself, or for anyone who uses this co	mputer:
 <u>⊾</u>veryone Iust <u>m</u>e 	
Cancel	< Back Next >

 Please review the License Agreement. If you agree, select "I Agree" and click Next.



6. BookSnap software will be installed.

) BookSnap			🛛
Installing BookSnap			Ô
BookSnap is being installed.			
Please wak			
	[]		
	Cancel	< <u>B</u> ack	<u>N</u> ed 2

7. After installation of BookSnap software is complete, select **Close** (to proceed to install another software).



8. The Welcome screen to BookDrive Editor will appear.



9. Review the License Agreement. If you agree, select "I Agree" and hit Next.

🛃 BookDrive Editor 3	
License Agreement	
Pease take a moment to read the licens Agree", then "Nexi". Otherwise click "C	ss agreement now. If you accept the terms below, dick " annel".
BookDrive Editor 3	<u> </u>
PLEASE READ CAREFULLY BEFOR	REINSTALLING
DookDrive Editor Software License A	Agreement
◯ I <u>D</u> o Nol Agree	€ Agree
	Cancel < <u>B</u> ack <u>N</u> ext >

10. Proceed until the installation is complete.

🛃 BookDrive Editor 3		
Installing BookDrive Editor 3		
BookDrive Editor 3 is being installed.		
Please wet		
	rcel (Kack	Next >

11. It will appear like this when the installation of BookDrive Editor is complete.





Click **Close** and then **OK**.

12. BookSnap and BookDrive Editor shortcuts will now appear on your desktop.



13. Remove the disk from the computer's drive.



After the software installation is complete, next step is to activate the software.

Double click BookSnap icon on desktop to open the BookSnap program.	BookSnap	BookDrive Editor 3
	🦺 start	🧻 🥥 🥘

1. After opening the program, you will see the following dialog that asks for registration.

roduct	Registration 🛛 🛛 🔀
R	BookSnap Trial version. Expire in 15 days.
В	IV NOW ! Later
Registr	ation Code
G	et Activation Code From The Internet
Activat	ion Code
	Activate

2. Please fill in your **Registration Code**. (Your Registration Code is located on the back of your CD case)

3. Once you have filled in the Registration Code, click **Get Activation Code From The Internet.**

Product Registration
BookSnap Trial version, Expire in 15 days,
Buy now ! Later
Registration Code GGMM-7WXF-SFFK-9PKF
Get Activation Code From The Internet
Activation Code
Activate

4. You will be redirected to Atiz online registration page.

Please fill in your information.

Atiz will use this information to contact you in the future about the software upgrades when they are available. Once you have filled in the information completely, click **Submit**



5. The information will be sent to Atiz server. If your information and the Registration Code are correct, you will receive the Activation Code.

Attiz : Activation Successfu	il - Microsoft Internet Ex ir Jah	plorer					- 0
Back + (2) - 💽 💽	🔥 🗋 Swith 🔶 F	Favortes 🙆 📿 .	8	10 11 H	18		
iliets al interviewent attractment	activated.php		On the Part		- 	un * * •	
🗸 = 🔁 🔹 🌒 Alle i Activation	Se						• 3
	100						
	z						
home	how to eBook	products buy	support	company	TIERS	search P	
			Activ	ation	Cod		
			ACUV	auon	Cou		
Activat	ion Code:						
DEOT	5POLM\W	1					
PFUI	ODQJ-IVIV TU]					
(Please co	py and paste the activation	code into the software a	end click "Activate" bu	tion)			
Your In	formation						
Your inform	ution has been updated.						
- This regis	tration code has already be	en used.					
Firstname	Permikiat						
Lastname	Steening						
e-mail :	permisiat@satiz.co	0m					
Company:	ATIZ						
Street Addre	995:						
Cay :	Dangton						
5001001	(fideated)						
Bottware na	ene: BookSnapt						
Forgattration Activation C	ade PERT SBOLLENY	716-3190 Ø					
*We have e	mailed you this information	erran. . Please keep it sale for	future une.				
		24	353	74			
		blog to	nam press	contact us			
Stay up-to-de	ite on what's happening at As	iz.					
	ter vour enail address. Tutter			Copyright # 20	of Alls Innovation Co.	Ltd. All Rights Repartment	
					and the second sec	the second s	
6							

6. The Activation Code is used to activate your copy of the software. Copy your Activation Code and paste it on the Registration window.



Product Registration	
BookSnap Trial version. Expire in 15 days.	
Buy now ! Later	
Registration Code	
GGMM-7WXF-5FFK-9PKF	
Get Activation Code From The Internet	
Activation Code	Activicada in this has
PFOT-5BQJ-MVY0	Activide in this bo
Activate	

7. Click Activate and the program will finish the installation successfully.



Note: Once you are done with the activation of BookSnap software, repeat this process with the activation of BookDrive Editor software.



Scan.

www.atiz.com/support/booksnap



 Plug in the AC cord to the lamp. Make sure it is not connected to the power source and the switch is off.





2. Plug the AC cord into the power source (110VAC or 220VAC). The exact voltage rate depends on your country. Please also check the light bulb voltage rate before use.



 Mount the camera on the mounting area. Secure it firmly by tightening the screw.



6 Connect the USB cord to the camera.

3. Turn on the switch.



5 Make sure the center of the lens is on the guide line.



11. Cover the BookSnap platform with the shade.



8 Make sure the center of book is on the guide line.



10. Place the magnetic bookholder at the bottom of the book.



12. You have successfully installed the BookSnap!



1. Start BookSnap software by double clicking the program icon. The program will appear like this.



2. Please select whether you are going to use just one camera or two cameras to scan a book.



Select **Single Camera** if you have only one camera



Select **Double Cameras** if you have two cameras.



3. Next, select if you want page sequencing to go from left to right (this is the case for most countries) or from right to left (e.g. Japanese or Korean books, etc.)



4. Next, select file saving options.



5. After you are done with the Wizard, click **Next** to proceed to next stage where you will be able to change settings of the cameras, test the cameras and preview images.

6. To be able to change settings and shoot test images, the computer first needs to connect to the cameras.

Click **Acquire cameras**, BookSnap will search for any cameras that are currently connected with the computer.

			1
3 Language Help			
 No Device 	Acquire P	No Device	
	(Comments of the second secon		
•] • •]	0	e)	
0) • ·)	0 	0)	
e j + • j Novrg Main (3) Speed	0 10 10 10 10 10 10 10 10 10 10 10 10 10	⊕ j B ● j O Managafada W W W	
Different State	0 (Receiption)	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	
Contrary Mark Ministry Mark M Entrary M Entrary M	0 Marian Marian	⊕ j ⊕ ⊕ j O MarcyNob SD Sted ¥ Disect Ref ¥ Disect Ref ₩ m m	
Entrony Made To Speed Ministry Ministry Mi	C Bent	G J Colored Managetodo SE David W Dolares Rad W Dolares Rad	

IMPORTANT: Causes and solutions if BookSnap software could not find and acquire all the cameras you need. a) Check camera compatibility Unsupported cameras? Make sure that the camera model used in supported by BookSnap software b) Windows XP only for BookSnap software Is it Windows Vista? Currently, BookSnap is only compatible with Windows XP. c) Canon Drivers Where are drivers? Have you already installed drivers of the Canon cameras? If not, please install the drivers of the Canon cameras first. You can find them from the Canon CD that comes with the cameras or download from Canon website. d) USB Connection Please also ensure that the USB cables are properly connected between the camera and the computer. e) Camera is on Make sure the camera is turned on. f) <u>Batterv</u> Is the camera running low on battery? If this is the case, please recharge the battery and use a fully charged battery. g) Playback Mode Some camera models have a separate Playback mode. If this is the case, please set so that your camera is at Playback mode.

7. If the computer can locate the cameras, there will be a green sign showing that the cameras are now connected.





The red sign means that the cameras are still not connected. If this happens, make sure you have taken all the steps as shown in the previous page.

If the system still cannot acquire the cameras after following all the instructions, please contact Atiz for technical support.

As the cameras are acquired, the cameras will capture some sample shots and here is the page that you should see.



8. If the pages appear inverse like this, you can reverse them by clicking **Reverse** button and the pages will become reverse like this.



9. To conveniently adjust the relative position of the cameras and the position of the book, you can see live preview (it is like a video stream showing the current position of the page).



Preview button



During that time, it is easier for you to change the position of the camera and/or the position of the book. The video preview will help you easily get images straight on the screen.

10. There are some neat things you can do within the BookSnap software. For example, you can zoom in or zoom out. You can also adjust brightness and other settings of the cameras. What kind of settings you can adjust depends on the model of the cameras.



Metering Mode		ISO Speed	
Evaluative	~	Auto	¥
AF Distance		Flash	
Auto	~	Off	~

Most Canon camera models allow you to adjust the Metering Mode, ISO Speed, AF Distance and Flash of the cameras.

Note: For good picture quality purpose, flash should always be off in BookSnap.

11. To see what kind of images those settings will produce, click this button will let you shoot sample shots.

The sample shots will not be saved. They will be discarded as you test next sample shots.

Once you are satisfied with the images that the cameras can produce, proceed to the actual scanning process by hitting

The sample shots look ok. I'm now ready to scan.

Now it's time for some serious scanning.

12. This is the main interface of the program during scanning.



13. The process to scan a book is easy.

You just hit **Scan Button** and then turn a page, hit **Scan Button** again until completion.

If you are tired of button pressing, click **Auto Scan** to turn the Auto Scan mode on and have the program keeps shooting the images for you automatically.

14. If you want your images to be cropped at the same time during scanning, click **Crop Mode Button**.



The red rectangle line represents an area to be cropped. What's inside the rectangle will be kept. What's outside will be thrown away.

Click the **Crop&Scan** button to crop the currently shown images and to scan the next pages.

Click the **Crop** button to crop the currently shown images when having no more pages to scan.

Some shots are not great and some pages are missing and I want to correct.

15. You can do that by relying on the set of buttons that will allow you to fix the pages.



Replace

Use when you want to replace an existing image with a new one.

Examples:

- The images you got are not very clear.
- You got your hands in the shot.
- You haven't done turning pages yet.
- Page is creased and you want to replace

Use mouse to select the thumbnail of the image you want to replace. Then click **Replace**.

100	Δ.
	2.
_	Ζ.

Insert

Use when you have skipped a page and you want to insert a new page somewhere in between.

Use mouse to select the thumbnail of the image that you want to insert new pages in between. Then click **Insert**.



Create Spare

Sometimes you just want to have spare pages for comparison purpose so that you can select the best one to use at the end.

Use mouse to select the thumbnail of the image that you want to create its spare.

Note:

Under **Instant Crop**, the last page and the pages that are added using the **Replace**, **Insert** or **Create Spare** commands will not be cropped by the program.

You must do a little more to help crop those pages.

Steps:

1. Double click the thumbnail of the page that you want to crop manually and you will see the following dialog.



- 2. Click Crop Button
- 3. Set area you want to crop.
- 4. Click OK. Done.



Edit.

www.atiz.com/support/booksnap

Key Features of BookDrive Editor 3

J.	Rotation Rotates images to the correct orientation.
E	De-skew Compensates for image skew during scanning, resulting in straight images.
	Auto Level Automatically adjusts to the level in the histogram of the images to make them their color look smoother.
杠	Crops unwanted area of the images out.
X	Brightness and Contrast Allows the adjustment of brightness and the contrast of the images. Brightness and Contrast adjustment.
Δ	Sharpen Sharpening makes images look sharper. It brings out details that were not there before.
	Black border removal Eliminates the black edges typically generated by scanners with black backgrounds. It also reduces the file size while improving legibility.
	De-speckle Helps eliminate noise such as speckles and streaks that are either present on the original document or generated during the scan.
	Background removal Removes the unwanted, dirty or dusty background from the document and leave only clean and clear background.
R	Resize Images can be resized to any standard size or custom size.
	File storage and retrieval Supports TIFF, multi-page TIFF, PDF, JPEG file formats
	Image compression TIFF compressions: CCITT_G3, CCITT_G4, LZW JPEG compressions: JPEG Quality, LZW



Start BookDrive Editor software by double clicking the program icon. The program will appear and should look like this.



The main interface of the program consists of the left area and the right area. The left area lists all the source files to be processed. The right area is a preview panel, which will show output images as they are being processed.

To start, you need to add images to the program. You can do that by either selecting from the menu or simply click its button.

File	Left Page	Right	Page	Tools	Help
	Open	•	L	Left Pages	;
	Remove	•	R	Right Page	es
	Exit Alt+F4		LR	Both Page	s
c:l-	Left Deee	D:-L1	. D	Taala	l la la
File	Lert Page	Right	: Page	TOOIS	нер
		L&R		R	

There are many ways to add images to the program:

- 1. By selecting from the menu. Select File / Open / Left Pages, Right Pages, or Both Pages.
- By clicking the button. There are 3 buttons relevant here: the one showing "L" (meaning to add only the left pages); the one showing "L&R" (meaning to add both left and right pages); and the one showing "R" (meaning to add only the right pages)
- 3. By drag and drop. You can also drag and drop left images to the left column and drag and drop right images to the right column.



If you click the button, you should see this open window.

The open window allows you to select the files you want to add for processing.

To select many files, do a mouse drag or hold **Ctrl** while clicking on each image.

To select all, press Ctrl + A.

After select, click **Open**. The program will add those selected images and show their preview thumbnails.

BookDrive Editor	r1			
File Left Page II	light Page Tools H	nip		
	U1 A	<u>^</u>		
191 <u>1</u>	8 2-			
0032.JPG	0000.096	-		
SP 6	SD.			
0034.JPG	0035JPS			
0036.JPG	0037.PG			
_	_			
		STATUS: Sland by	STATUS: Standby	
		OUTPUT:	OUTPUT:	

How images are sorted and put in an order?

The software will automatically sort the selected images based on their file names. The ones with lower values will be on top. The ones with higher values will at the bottom.

If you select the both L&R page option, the program will sequentially put the first one on the left, the second one on the right, the third one on the left, the fourth one on the right, and so on until the last image.

Next step is to do settings.

Click Settings button.

You will see the Setting window as shown here:



This is the page where you set all the parameters to make the program produce the final images to your liking.

You do not have to do new settings every time you want to process images. BookDrive Editor allows you to save all those parameters in what is called a "**Profile**".

Once you have saved the Profile that contains the parameters that you want, next time that you use BookDrive Editor, just select the Profile that you save and open it for use.

The area that allows you to **open**, **save**, and **delete** a Profile looks like this:

Profile:	General Setting	-	Save As	-

Settings

To enable any image operation, just press the icon representing the intended image operation.

For example, this is what will appear if you want to enable image rotation.



Image rotation is disabled.



Image rotation is enabled.

Rotation



For rotation, you have options to select to rotate 0, 90, 180 or 270 degrees.

Example:







Before







Right page



Before





After





Deskew

Compensates for image skew during scanning resulting in straight images.



Select **Auto** if you don't know the exact degrees to rotate. Alternatively, you can manually set a value that you want the image to be rotated (between -15 to 15 degrees).





Auto Level

Automatically adjusts to the level in the histogram of the images to make them their color look smoother.





Crop

Crops unwanted area of the images out The cropping setting area looks like this:



Some available options under cropping image operation include:



Load another image to see its thumbnail related to cropping. Preview of how output will look like after cropping and padding. Copy the parameters of the left page to the right.

Copy the parameters of the right page to the left.





Note: The red rectangle that marks a crop area can be moved by a mouse drag.



Brightness and Contrast

Allows the adjustment of brightness and the contrast of the images.





Sharpen

Sharpening makes images look sharper. It brings out details that were not there before.

Before

2.3.2 Image Acqui

A geometry that is u an in-line arrangeme shows. The strip prov dicular to the strip Fig. 2.14(a). This is the ing devices with 4000 used routinely in airb mounted on an aircra ographical area to be





2.3.2 Image Acqui

A geometry that is u an in-line arrangeme shows. The strip prov dicular to the strip Fig. 2.14(a). This is the ing devices with 4000 used routinely in airb mounted on an aircra ographical area to be



Black border removal

Eliminates the black edges typically generated by scanners with black backgrounds. It also reduces the file size while improving legibility.





De-speckle

Helps eliminate noise such as speckles and streaks that are either present on the original document or generated during the scan.





Background removal

Removes the unwanted, dirty or dusty background from the document and leave only clean and clear background.





Resize

Images can be resized to any standard size or custom size.

Resize

Images can be resized to any standard size or custom size.





Output file selection

- OUTPUT PAR	AMETER :
Format:	Jpeg 🔽
Jpeg Quality:	100 🚔
Resolution:	300 💌
Color Depth:	B&W 🗸
_ Threshold —]
Automatic	~
	128

- The available output format options are TIFF or JPEG.
- Available compressions for TIFF are LZW, CCITT G3, CCITT G4
- Users can also select the level of compression for JPEG format by setting its quality level.
- Resolution is where you can set DPI of the output image. You can select 100, 200, 300, 600 DPI or specify the exact desired DPI.
- Available color options are: Black and White, Grayscale and Color.
- As for Black and White conversion, there are many types of conversions allowed. This has to do with the threshold of how a given a pixel is converted to either a black or white pixel.
 - Fixed (threshold value is set at 128)
 - User defined (users can define other threshold values)
 - Automatic (the level of optimal threshold will automatically be selected by the computer).
 - Highest Quality (this setting can be known as dynamic localized thresholding, which means there can be many thresholding values on a page. If selected, the program will scan the entire page and automatically adjust the thresholding values for optimal values throughout the pages. This setting will take the longest time but will provide the best quality.)



Run batch

Once all the settings have been made, it's time to run the batch image processing operations. Simply hit the Run Batch button.



If you want to stop, click the same button again.



Creating PDFs

BookDrive Editor 3 and BookSnap can create PDFs or Multipage TIFF by clicking the **PDF** button. Once clicked, you will see the following window.

ittple Document Mana	fet.		19/8 C
iles to PDF			Format
Fie tipe	Son Pat	Add Fodia Add Fodia Add File Add File Add File Add Fodia Add	Corpession State at Pin Hone Corpession State St
e1 =			
why whiple Document Manu	uger .		Create Break Canad
als altiple Decument Manu 8 Filles to PDF	que .		Create Break Canton
eb ships Decument Mass 8 Flots to PDF Flat Name 00 pp 00 ppp	Sar Path 25.84 Path 25.84 PC 25.84 PC 25.94 PC 25.9	Addram Se Addram Se Rosson Se Up Se Dom	Cease Deep Canon
ab abipto Decument Man B Files to PDF File Man Color Dy Color	Ein Puh Stern B. Observation and EntropOlic Stern B. Observation and Entr	الله مطالعة الله مطالعة	Cease Dees Cane

<u>Steps</u>

- 1. Click **PDF** button.
- 2. Select the images you want to export to PDF.
- 3. Select the output format (PDF or TIFF) and other parameters.
- 4. Click Create.

© Copyright 2008 Atiz Innovation Co., Ltd.